Linear

KIISS E020
Installation Guide

PRODUCT CARE AND HANDLING

- KKDC products are delivered in appropriate packaging. Any handling instructions on the packaging must be observed. Products should remain in packaging 'as delivered' until installation or for ongoing transportation and storage.
- Inspect products carefully before installation. Do not proceed to install any product that may have been damaged in transportation, storage or handling.
- Handle with care. Many KKDC products contain precision electrical components and are not designed to withstand excessive stresses from tension or compression.
- Please follow standard ESD (Electrostatic discharge) protection measures when handling and installing KKDC LED products.

SAFETY AND WARRANTY

- Installation is only to be carried out by suitably qualified persons in accordance with installation instructions and all applicable regulations or standards. (Improper installation can create an electrical hazard with risk of electric shock, fire or injury).
- KKDC will not be held responsible for any consequences arising from improper product handling, storage or installation.
- KKDC products must be installed as supplied. Disassembly, modification or attempted repair will invalidate warranty and may create an electrical hazard.
- The KKDC product warranty is available with this document or on our website – **www.kkdc.lighting**.

PREPARATION

- Install KKDC products in accordance with the Wiring and Mounting instructions supplied with the product, using the recommended accessories, tools and fixings where specified.
- Product specification and installation information is also available from the KKDC website **www.kkdc.lighting**.
- Products should only be installed in areas appropriate to their IP rating, operable temperature and humidity range.
- Carefully plan and check the physical layout and circuit structure of the installation before starting work. Note wiring methods, cable type and connection points along with positioning and rating of power supplies and any control gear. Refer to all product information – including that for power supplies/control gear – and confirm choice of power supply, control gear, cable thickness and cable length.
- For safe and reliable operation KKDC LED products must only be used with suitable KKDC supplied or recommended power supplies and control gear. Contact KKDC for further information.
  (North America – Use only UL listed Class 2 power supplies with KKDC products – See also Installation Guide – Wiring)
- The KKDC LED products in this guide require **12V DC** or **24V DC** 'constant voltage' power supplies as indicated in product specifications.

AFTER INSTALLATION

- KKDC products are designed to be maintenance free however accumulated dust may be removed from the emitting surface of luminaires with careful use of a soft dry cloth.
- Ensure that paints, organic solvents and caustic or corrosive cleaning chemicals do not come into contact with KKDC products.
  For example **DO NOT USE** –
  - Benzene, Toluene, Xylene, Acetone, Carbon tetrachloride, Gasoline, Ether,
  - Sodium/Calcium hydroxide, Sodium Carbonate.
- For cleaning or sanitization – products in sealed IP rated housings may be wiped with a soft cloth dampened with an alcohol cleaner or with cool, soft water diluted (5% or less) bleach (Sodium Hypochlorite) solution.
- Please retain this information and pass to those responsible for installation/site maintenance.

Linear

Earth ground continuity test
After Installation

KKDC

CONTINUITY TESTING

After installing the product, a short to the ground may cause damage to the product.
To ensure safe use of the product, please check the following three points.

Product connection flow chart

1. Continuity test between earth ground and DC_24V

1.1 Set the DMM function to resistance measurement position, and perform EG and DC_24V continuity test.

1.2 Normal if infinity or tens of MΩ (xx MΩ) is measured.

2. Continuity test between earth ground and DC_GND

2.1 Set the DMM function to resistance measurement position, and perform EG and DC_GND continuity test.

2.2 Normal if infinity or tens of MΩ (xx MΩ) is measured.

3. Continuity test between earth ground and controller CH "n"

3.1 Set the DMM function to resistance measurement position, and perform EG and controller CH "n". (All CHs connected to the controller undergo continuity test).

3.2 Normal if infinity or tens of MΩ (xx MΩ) is measured.

3.3 If no controller is used, 3 can be omitted.

The reasons for checking the procedures 1-3 above are as follows.

The figure on the right shows the results of applying HLG-600H-24A/meanwell to the SMPS in the Product Connection Flowchart and measuring the voltage between Earth Ground and DC_24V at the DMM AC voltage measurement location.

Depending on the SMPS model applied, the voltage may not be measured, but the voltage may be higher.

If there is no problem with the 1-3 procedure, there is no problem, but if there is a problem with the 1-3 procedure, it can lead to a long-term defect, so a confirmation process is needed.

Linear

KIISS E020
Installation Guide

READ BEFORE INSTALLATION

- The mounting surface to which any KKDC product is attached must not carry any electrical potential and metallic surfaces must be earthed. Avoid physical contact between adjacent LED products.
- Prepare, measure and mark the installation location and mounting surfaces before fixing.
  Any machining or drilling etc. should be completed before mounting. KKDC products and their immediate installation area should be kept clean and dry and free of paints and solvents during and after installation.
- Ensure that products are mounted with supplied, recommended or appropriate screws and fixings to suit the surface material.
- Mount products so that cables and connectors will not come under excessive stress and position accessories, wiring and connectors where they will not cast shadows (particularly when joining TIMI RGB which has four wire connectors).
- North America – UL certification advice:
  Caution – To reduce risk of fire, do not install in any sealed compartment smaller than:
  300mm (12 inches) x 300mm (12 inches) x Length of KIISS E020

POWER FEED CONNECTION

1 Access power conductors underneath product.



2 To attach WAGO connectors push lever up and slide onto power conductor. Push lever down to lock.



3 Connect to 24V DC power supply wires (There is no polarity).

CONCEALED CLIP

1 Fix clips with suitable screws (min. 3 clips per metre/40").

2 Align product with clip.



3 Press product firmly in place.

Note: This guide is produced from testing under 'average' conditions and does not represent all possible applications or installation circumstances.
Please contact KKDC for further information.
KKDC may change product specifications and installation guidance without prior notice.

Linear

KIISS E020
Installation Guide

END-TO-END CONNECTION

1

Prepare two product ends and two quick-release in-line WAGO connectors.



2

To attach WAGO connectors push lever up and slide onto power conductor. Push lever down to lock.



3

Repeat process to join products.

4

Align joined products over concealed clips (Allow 3 per/m).

5

Push down firmly to locate in place.

6

Ensure products are pushed tightly together to avoid light leak gap.

Note: This guide is produced from testing under 'average' conditions and does not represent all possible applications or installation circumstances.
Please contact KKDC for further information.
KKDC may change product specifications and installation guidance without prior notice.

Linear

KIISS E020
Installation Guide

E020 - LED MODULE REMOVAL

1 Release snap-on cover.

2 Remove crosshead screws securing LED Module to product housing.

3 Slightly tilt LED module carefully using screwdriver if needed.

4 Lift out LED module.

5 Module is ready for return.

Reverse process to install new LED module.

Note: This guide is produced from testing under 'average' conditions and does not represent all possible applications or installation circumstances.
Please contact KKDC for further information.
KKDC may change product specifications and installation guidance without prior notice.

Linear

E020 + 100W PSU

Installation Guide – Wiring

READ BEFORE INSTALLATION

- Cables used for connecting KKDC products must be of a suitable type and recommended gauge. Cable insulation must remain undamaged and conductors free from dirt and corrosion.
- Control cables should be of a suitable shielded type and not fixed in proximity to high voltage power cables or other sources of electromagnetic interference.
- When connecting KKDC products always observe the correct polarity (+/-). Failure to do so may destroy the product.
- Electrical circuits should be wired with power off and all wiring and connections should be complete and checked thoroughly before power is switched on. Take particular care not to confuse any control and power wiring. Do not remove any supplied product cable labels.
- Power supplies should not be made 'live' without the correct load attached and the low voltage output must not be switched. Do not exceed the recommended load.
- Remove only the minimum of cable insulation necessary to make wiring connections to eliminate the possibility of short circuit.
- Cables should be joined with terminal blocks and adequately protected against water immersion or moisture ingress with suitable tapes and sealants, potting compounds and IP rated junction boxes as appropriate to the installation and operating environment.
- The LED products in this guide require **24V DC** (constant voltage) Class 2 power supplies (UL listed – for North America).
- When connecting **E020** products end to end – **Do not exceed 10m/32.8ft** (from any one parallel power feed – see wiring examples).
- **IMPORTANT UL COMPLIANCE NOTE:** Wiring cannot be used in areas covered by UL because Class 2 power supplies **OVER 100W** are **NOT** permitted in those areas.

WIRING EXAMPLES

Switched

	Cable size / Max distance (d)				
	0.5mm²/ 20AWG	0.75mm²/ 18AWG	1.0mm²/ 17AWG	1.5mm²/ 15AWG	2.5mm²/ 13AWG
E020 (4m/13.12ft) + 100W PSU	11.5m/37ft	17.0m/55ft	23.0m/75ft	34.5m/113ft	57.5m/188ft



1-10V Dimming

	Cable size / Max distance (d)				
	0.5mm²/ 20AWG	0.75mm²/ 18AWG	1.0mm²/ 17AWG	1.5mm²/ 15AWG	2.5mm²/ 13AWG*
E020 (4m/13.12ft) + 100W PSU + 1-10V Dimming	10.0m/32ft	15.0m/49ft	20.5m/67ft	30.5m/100ft	51.5m/168ft



(max 50m/164ft @ 22 AWG)

Note: This guide is produced from testing with KKDC approved power supplies or control gear.
Performance with other power or control products cannot be guaranteed. Contact KKDC for further information.
KKDC may change product specifications and installation guidance without prior notice.

Linear

E020 + 100W PSU

Installation Guide – Wiring

DALI Dimming

	Cable size / Max distance (d)				
	0.5mm²/ 20AWG	0.75mm²/ 18AWG	1.0mm²/ 17AWG	1.5mm²/ 15AWG	2.5mm²/ 13AWG*
E020 (4m/13.12ft) + 100W PSU + DALI Dimming	9.5m/31ft	14.5m/47ft	19.5m/63ft	29.5m/96ft	49.5m/162ft

*KKDL-02 only



(max 50m/164ft @ 22 AWG)

DMX Dimming

	Cable size / Max distance (d)				
	0.5mm²/ 20AWG	0.75mm²/ 18AWG	1.0mm²/ 17AWG	1.5mm²/ 15AWG	2.5mm²/ 13AWG*
E020 (4m/13.12ft) + 100W PSU + DMX Dimming	9.5m/31ft	14.5m/47ft	19.5m/63ft	29.5m/96ft	49.5m/162ft



(max 50m/164ft @ 22 AWG)

Note: This guide is produced from testing with KKDC approved power supplies or control gear.
Performance with other power or control products cannot be guaranteed. Contact KKDC for further information.
KKDC may change product specifications and installation guidance without prior notice.

Linear

E020 + 240W PSU

Installation Guide – Wiring

READ BEFORE INSTALLATION

- Cables used for connecting KKDC products must be of a suitable type and recommended gauge. Cable insulation must remain undamaged and conductors free from dirt and corrosion.
- Control cables should be of a suitable shielded type and not fixed in proximity to high voltage power cables or other sources of electromagnetic interference.
- When connecting KKDC products always observe the correct polarity (+/-). Failure to do so may destroy the product.
- Electrical circuits should be wired with power off and all wiring and connections should be complete and checked thoroughly before power is switched on. Take particular care not to confuse any control and power wiring. Do not remove any supplied product cable labels.
- Power supplies should not be made 'live' without the correct load attached and the low voltage output must not be switched. Do not exceed the recommended load.
- Remove only the minimum of cable insulation necessary to make wiring connections to eliminate the possibility of short circuit.
- Cables should be joined with terminal blocks and adequately protected against water immersion or moisture ingress with suitable tapes and sealants, potting compounds and IP rated junction boxes as appropriate to the installation and operating environment.
- The LED products in this guide require **24V DC** (constant voltage) Class 2 power supplies (UL listed – for North America).
- When connecting **E020** products end to end – **Do not exceed 10m/32.8ft** (from any one parallel power feed – see wiring examples).
- **IMPORTANT UL COMPLIANCE NOTE:** Wiring cannot be used in areas covered by UL because Class 2 power supplies **OVER 100W** are **NOT** permitted in those areas.

WIRING EXAMPLES

Switched

	Cable size / Max distance (d)				
	0.5mm²/ 20AWG	0.75mm²/ 18AWG	1.0mm²/ 17AWG	1.5mm²/ 15AWG	2.5mm²/ 13AWG
E020 (10m/32.81ft) + 240W PSU	-	3.5m/11ft	5.0m/16ft	7.5m/24ft	13.0m/42ft



1-10V Dimming

	Cable size / Max distance (d)				
	0.5mm²/ 20AWG	0.75mm²/ 18AWG	1.0mm²/ 17AWG	1.5mm²/ 15AWG	2.5mm²/ 13AWG*
E020 (10m/32.81ft) + 240W PSU + 1-10V Dimming	7.0m/22ft	10.5m/34ft	14.5m/47ft	21.5m/70ft	36.5m/119ft



Note: This guide is produced from testing with KKDC approved power supplies or control gear.
Performance with other power or control products cannot be guaranteed. Contact KKDC for further information.
KKDC may change product specifications and installation guidance without prior notice.

Linear

E020 + 240W PSU

Installation Guide – Wiring

DALI Dimming

	Cable size / Max distance (d)				
	0.5mm²/ 20AWG	0.75mm²/ 18AWG	1.0mm²/ 17AWG	1.5mm²/ 15AWG	2.5mm²/ 13AWG*
E020 (10m/32.81ft) + 240W PSU + DALI Dimming	7.0m/22ft	10.5m/34ft	14.0m/45ft	21.0m/68ft	35.0m/114ft

*KKDL-02 only



DMX Dimming

	Cable size / Max distance (d)				
	0.5mm²/ 20AWG	0.75mm²/ 18AWG	1.0mm²/ 17AWG	1.5mm²/ 15AWG	2.5mm²/ 13AWG*
E020 (10m/32.81ft) + 240W PSU + DMX Dimming	7.0m/22ft	10.5m/34ft	14.0m/45ft	21.0m/68ft	35.0m/114ft



Note: This guide is produced from testing with KKDC approved power supplies or control gear.
Performance with other power or control products cannot be guaranteed. Contact KKDC for further information.
KKDC may change product specifications and installation guidance without prior notice.

Product Warranty

We believe we produce a superior product, and that your investment should be rewarded with years of trouble free operation. Through rigorous quality control and testing at every stage of manufacture we are confident that KKDC products will operate as intended. In the unlikely event that purchasers should experience a product failure, this should in the first instance be dealt with by contacting the supplier or local authorised KKDC representative. Our warranty is provided in addition to any statutory legal rights and details the terms under which claims can be made.

1. Warranty Period

The Company guarantees the Products against defects in materials and workmanship for a period of ten (10) years from the date of dispatch, provided that the initial installation is carried out by personnel suitably qualified and strictly in accordance with the Company's installation instructions.

This Warranty is personal to the original purchaser and to the premises at which the Products were first installed and may not be assigned or transferred.

2. Second-Life Return & Renewal

Customers may return Products to the Company for modification or upgrade to meet new site requirements ("Renewal Service"). Renewal Service must be requested in writing and approved by the Company prior to commencement.

Products that have undergone Renewal Service shall remain subject to the original Warranty Period, which shall not be extended or restarted beyond the initial ten-year term.

3. Second-Life On-Site Modifications

Where the Customer wishes to modify the Product on site to accommodate a new site arrangement, such modifications shall be carried out strictly in accordance with the Company's installation instructions.

Any alteration requiring disconnection or modification of the mains electrical circuits must be performed by a suitably qualified electrician authorised by the Company. To the extent that modifications may be effected without disturbing the mains circuits, the Customer may undertake such work.

Notwithstanding the foregoing, any defect or failure arising from second-life modifications shall render this Warranty null and void. Only Products modified in strict compliance with the installation instructions shall continue to be covered for the remainder of the original Warranty Period.

4. Repair/Replacement

Should a KKDC product fail to function within the warranty period, KKDC will on its sole discretion provide a replacement free of charge or repair defective components in accordance with the terms set out below. Purchasers shall bear the cost of removal and return of any product subject to a warranty claim and that of installing a replacement. Any other costs, including but not limited to replacement costs upon installation; costs caused from failures of the installation or other damages and/or consequential damages are not covered by this warranty. Replacement products shall as far as possible match the specification of the original but may have superior performance characteristics in line with ongoing product development.

5. Return of defective Product

The purchaser making a warranty claim shall contact KKDC (or their authorised representative) at the earliest opportunity to be provided with an address for return of the product. On receipt of returned product/s the validity of the claim will be checked. Proof of purchase may be required. KKDC reserve the right to conduct diagnostic examination of any defective or failed product to determine patterns of usage and cause of failure and reserve the right to be the sole judge as to whether a returned product is defective within the terms of this warranty.

6. Notes / Conditions of Warranty

This warranty applies only to defects in materials and workmanship and only where KKDC Products are properly handled, stored, installed, wired and maintained in accordance with the most recent published KKDC product usage guides, installation instructions, specification sheets, and any applicable local electrical safety standards and wiring regulations. (The most recent versions of KKDC product documentation are available from the website - **www.kkdc.lighting**).

This warranty does not constitute any inference as to the suitability of any product for any purpose. In no event shall KKDC be liable for any other costs or damages including lost profits, incidental, special or consequential damages.

Warranty will not apply in the event of;

Product damage due to abuse, unauthorised alteration, modification, accident, natural disasters and acts of God.

6.1 Initial product installation by unqualified persons (1st life).

6.2 Unauthorised product modification, disassembly or attempted repair by non KKDC staff.

6.3 Product installation or storage in 'abnormal' conditions or locations, including but not limited to those where:

- Ambient Temperatures are in excess of 50°C (please refer to precise specification for each product).
- There is excessive humidity.
- Any product has been subjected to excessive mechanical stress, or physical damage.
- Inadequate heat sinking is provided for any unhoused 'bare PCB' type LED product.
- IP67 class luminaires are installed without adequate local drainage, or become immersed in water.

6.4 Chemical contamination or damage from salt laden air.

6.5 Damage from use of pressure washers or other mechanical cleaners.

6.6 Improper use of 'sanitizing products' and maintenance using improper or unapproved chemical compounds/solvents.

6.7 Unauthorised use of parts or accessories not manufactured by KKDC in conjunction with KKDC Products.

6.8 'Constant Voltage' (CV) KKDC LED Products are supplied with incorrect voltage.

6.9 'Constant Current' (CC) KKDC LED products are supplied with incorrect current.

6.10 Incorrect layout, cutting and connection of wiring; intermittent or improper mains electrical supply.

6.11 Product/s having damaged serial number, cable or Certificate labels.

Note: KKDC reserves the right to make changes to product specifications and installation guidance without prior notice.

Product Warranty

6.12 Product/s which have been installed more than once or have not been returned promptly and directly to KKDC for fault diagnosis and testing.
6.13 Product/s discoloured and/or deformed due to the natural environment and lifetime.
6.14 Product/s installed in special/extreme environmental conditions (Such as: in Sub-zero polar regions / in desert regions on the equator / underwater deeper than 5m).
6.15 Product/s not installed in accordance with KKDC installation and wiring guides.

7. Warranty contacts

Warranty claims within the REVO family can be made by anyone by contacting KKDC or local KKDC authorised representative details of which can be found via the supplier or on the website – **www.kkdc.lighting**

8. Implied Terms

8.1 Subject to sub-clause 6.2, any condition or warranty which would otherwise be implied is excluded.
8.2 Where legislation implies any condition or warranty, and that legislation avoids or prohibits provisions in a contract excluding or modifying the application of or exercise of or liability under such condition or warranty, the condition or warranty shall be deemed to be included in this warranty. However the liability of KKDC for any breach of such condition or warranty shall be limited, at the option of KKDC, to the following:

If the breach relates to any KKDC Product:

(a.) the replacement or the supply of equivalent KKDC Product;
(b.) repair of product (excluding costs of removal and installation);
(c.) payment of the cost of replacement or of acquiring equivalent product; or
(d.) payment of the cost of repair of product (excluding costs of removal and installation).